

# S2 Dust extractor



Article code	Voltage
S201-EU	230 V, 50 Hz

Technical data	
Motor	2×1200 W
Amperage	11.8 A
Air flow	400 m <sup>3</sup>
Vacuum	22 kPa
Pre filter	Conical polyester
Pre filter surface	3 m <sup>2</sup>
HEPA filter	H13
HEPA filter surface	2.4 m <sup>2</sup>
Jet puls filter cleaning	Yes
Collection	Longopac

Equipped with	
2-stage industrial by pass motors	
Conical polyester Pre filter	
Hepa13 rated Hepa filter	
Jet puls filter cleaning	
7,5m 2" hose	
3 piece 2" wand	
Floor tool with rubber blades	
Longopac collection	

Physical parameters	
Weight	52 Kg
Size	786×547×1272 mm

## Pairing with Von Arx machines

With VA 10 L	With FR 200	With FG 250 S

# Spare parts

<p><b>Conical prefilter - 7500016</b></p> 	<p><b>Hepa filter - 7500000</b></p> 	<p><b>Longopack - 7500017</b></p> 
<p><b>Longopac holder - 7000016</b></p> 	<p><b>3 piece 2" wand-7500142</b></p> 	<p><b>Floor tool - 7500143</b></p> 
<p><b>Rubber squeegee, pair - 7509996</b></p> 	<p><b>Hose end cuff 2" - 7500018</b></p> 	<p><b>Connector D51 hose with V sealing - 800161</b></p> 
<p><b>Hose set D50 mm x 7,5m- 7001064</b></p> 	<p><b>Front casters - 7500165</b></p> 	<p><b>Rear wheels - 7500014</b></p> 
<p><b>SOFT START S2, 230 V / 120 V - 7500172</b></p> 	<p><b>MOTOR SET S2/S3, 230 V - 800180</b></p> 	<p><b>On/Off switch - 7500001</b></p> 