


Certificate of Conformity

Certificate Number: CN-PV-200047

On the basis of the tests undertaken, the samples of the below product have been found to comply with the requirements of the referenced specifications /standards at the time the tests were carried out. It does not imply that Intertek has performed any surveillance or control of the manufacture. The manufacturer shall ensure that the manufacturing process assures compliance of the production units with the examined products mentioned in this certificate.

Applicant:	SHENZHEN GROWATT NEW ENERGY TECHNOLOGY CO., LTD 1st East & 3rd Floor of Building A, Building B, Jiayu Industrial Park, #28, GuangHui Road, LongTeng Community, Shiyan Street, Baoan District, Shenzhen, P. R. China
Product:	Hybrid inverter / AC Coupled inverter
Ratings & Principle Characteristics:	See Appendix to Certificate of Conformity
Models:	SPH 4000TL3 BH, SPH 5000TL3 BH, SPH 6000TL3 BH, SPH 7000TL3 BH, SPH 8000TL3 BH, SPH 10000TL3 BH SPA 4000TL3 BH, SPA 5000TL3 BH, SPA 6000TL3 BH, SPA 7000TL3 BH, SPA 8000TL3 BH, SPA 10000TL3 BH
Brand Name:	Growatt
Tested according to:	IEC 61727:2004 Photovoltaic (PV) systems – Characteristics of the utility interface IEC 62116:2014 Test procedure of islanding prevention measures for utility-interconnected photovoltaic inverters
Certificate Issuing Office Name & Address:	Intertek Testing Services Ltd. Shanghai 2/F (West Side), No. 707, Zhangyang Road, Free Trade Experimental Area, Shanghai, P. R. China
Test Reports No:	180820113GZU-001 180820113GZU-002

Additional information in Appendix.



Signature

Certification Manager: Grady Ye

Date: 1 June 2020

This Certificate is for the exclusive use of Intertek's client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this Certificate. Only the Client is authorized to permit copying or distribution of this Certificate. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek.

APPENDIX: Certificate of Conformity

This is an Appendix to Certificate of Conformity Number: CN-PV-200047

Ratings &
Principle
Characteristics:

Model	SPH 4000 TL3 BH	SPH 5000 TL3 BH	SPH 6000 TL3 BH	SPH 7000 TL3 BH	SPH 8000 TL3 BH	SPH 10000 TL3 BH
Input data(DC)						
Max. recommended PV power (for module STC)	5200W	6500W	7800W	9100W	10400W	13000W
Max. DC voltage	1000V	1000V	1000V	1000V	1000V	1000V
Start voltage	120V	120V	120V	120V	120V	120V
Nominal voltage	600V	600V	600V	600V	600V	600V
MPP voltage range	120~1000V	120~1000V	120~1000V	120~1000V	120~1000V	120~1000V
No. of MPP trackers	2	2	2	2	2	2
No. of PV strings per MPP trackers	1	1	1	1	1	1
Max. input current per MPP trackers	12A/12A	12A/12A	12A/12A	12A/12A	12A/12A	12A/12A
Max. short-circuit current per MPP trackers	15A/15A	15A/15A	15A/15A	15A/15A	15A/15A	15A/15A
Output / Input data(AC)						
AC nominal power	4000W	5000W	6000W	7000W	8000W	10000W
Max. AC apparent power	4000VA	5000VA	6000VA	7000VA	8000VA	10000VA
Nominal AC voltage	3W+N+PE , 230V/400V;					
AC grid frequency	50/60Hz;					
Max. output current	6.1A	7.6A	9.1A	10.6A	12.1A	15.2A
Power factor	0.8leading ~ 0.8lagging					

This Certificate is for the exclusive use of Intertek's client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this Certificate. Only the Client is authorized to permit copying or distribution of this Certificate. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek.

APPENDIX: Certificate of Conformity

This is an Appendix to Certificate of Conformity Number: CN-PV-200047.

Ratings &
Principle
Characteristics:

Stand alone(AC power)						
AC nominal output power	4000W	5000W	6000W	7000W	8000W	10000W
Max. AC apparent power	4000VA	5000 VA	6000 VA	7000 VA	8000 VA	10000 VA
Nominal AC voltage	3W+N+PE , 230V/400V;					
Nominal AC frequency	50/60Hz					
Max. output current	6.1A	7.6A	9.1A	10.6A	12.1A	15.2A
Battery data (DC)						
Battery voltage range	100~550V					
Max. charging / discharging current	25A					
Continuous charging / discharging power	4000W	5000W	6000W	7000W	8000W	10000W
Type of battery	lithium battery / Lead-acid battery					
Capacity of battery	5~50kWh					
Others						
Technology	Transformerless					
Protection degree	IP 65					
Operating temperature range	-25 °C ~ +60 °C With derating above 45 °C					
Pollution degree	III					
Protective Class	Class I					
Software Version	YA1.0					

This Certificate is for the exclusive use of Intertek's client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this Certificate. Only the Client is authorized to permit copying or distribution of this Certificate. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek.

APPENDIX: Certificate of Conformity

This is an Appendix to Certificate of Conformity Number: CN-PV-200047.

Ratings &
Principle
Characteristics:

Model	SPA 4000 TL3 BH	SPA 5000 TL3 BH	SPA 6000 TL3 BH	SPA 7000 TL3 BH	SPA 8000 TL3 BH	SPA 10000 TL3 BH
Output / Input data(AC)						
AC nominal power	4000W	5000W	6000W	7000W	8000W	10000W
Max. AC apparent power	4000VA	5000VA	6000VA	7000VA	8000VA	10000VA
Nominal AC voltage	3W+N+PE , 230V/400V;					
AC grid frequency	50/60Hz					
Max. output current	6.1A	7.6A	9.1A	10.6A	12.1A	15.2A
Power factor	0.8leading ~ 0.8lagging					
Stand alone(AC power)						
AC nominal output power	4000W	5000W	6000W	7000W	8000W	10000W
Max. AC apparent power	4000VA	5000 VA	6000 VA	7000 VA	8000 VA	10000 VA
Nominal AC voltage	3W+N+PE , 230V/400V;					
Nominal AC frequency	50/60Hz					
Max. output current	6.1A	7.6A	9.1A	10.6A	12.1A	15.2A
Battery data (DC)						
Battery voltage range	100~550V					
Max. charging / discharging current	25A					
Type of battery	lithium battery / Lead-acid battery					
Capacity of battery	5~50kWh					
Others						
Technology	Transformerless					
Protection degree	IP 65					
Operating temperature range	-25 °C ~ +60 °C With derating above 45 °C					
Pollution degree	III					
Protective Class	Class I					
Software Version	YH1.0					

This Certificate is for the exclusive use of Intertek's client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this Certificate. Only the Client is authorized to permit copying or distribution of this Certificate. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek.