

## P1 Indoor PIR Sensor 17W



### Productspecificaties

Artikel nummer	<b>LL-P1-12-17-IN-PIR</b>
Wattage	<b>17W</b>
IP-Waarde	<b>IP 20</b>
Input	<b>AC230V</b>
Kleur temperatuur	<b>Tri-color (3000k-4000k-5000k)</b>
Bundel	<b>120 graden</b>
Driver	<b>Boke Flicker Free</b>
Chip	<b>SMD 2835</b>
Lumen	<b>2040lm</b>
Afmeting	<b>1200x55x60mm</b>
Gatmaat	<b>N.V.T.</b>

### Technische specificaties

CRI	<b>80</b>
Macadam	<b>&lt;3 SDCM</b>
Efficiency	<b>120lm/w</b>
Product life minimum	<b>50.000h L80 B10/70.000h L70 B10</b>
Chip	<b>SMD 2835</b>
Driver	<b>Boke Flicker Free</b>
Diffuser	<b>IK02</b>
TA	<b>-20C TA/max</b>
Powerfactor	<b>0,96</b>
UGR	<b>22</b>
Certificaten	<b>CE/LSOH/ENEC</b>