JS/WERLINE C

Hobby Glue Gun

15(40)W UK





Register online: silverlinetools.com





Version date: 01.03.2023

Introduction

Thank you for purchasing this Silverline product. This manual contains information necessary for safe and effective operation of this product. This product has unique features and, even if you are familiar with similar products, it is necessary to read this manual carefully to ensure you fully understand the instructions. Ensure all users of the product read and fully understand this manual. Keep these instructions with the product for future

Technical Abbreviations Key

~:	Alternating current
Hz:	Hertz
W:	Watts
min:	Minutes
g/min:	Grams per minute
3	

Specification

Input Voltage:	230V~ 50Hz
Max Power:	40W
Min Power:	15W
Pre-heating Time:	3-5min
Flow of Glue:	5-9g/min
Glue Stick Size:	11.2 x 100mm

As part of our ongoing product development, specifications of Silverline products may alter without notice.

Carefully read and understand this manual and any label before use. Even when used as prescribed it is not possible to eliminate all residual risk

Glue Gun Safety

⚠ WARNING: Always use safety goggles and work in a well-ventilated area when using this device.

A WARNING: Do not touch the Nozzle (1) or the molten adhesive. Both will be extremely HOT during, and for some time, after use.

WARNING: Noxious and irritating fumes may be released when heating glue sticks. Molten material may cause burns.

- This appliance can be used by children aged from 8 years and above and persons with reduced physical, sensory or mental capabilities or lack of experience and knowledge if they have been given supervision or instruction concerning use of the appliance in a safe way and understand the hazards involved. Children shall not play with the appliance. Cleaning and user maintenance shall not be made by children without supervision.
- Only use glue sticks of the correct size (11.2 x 100mm) for this product
- . Insert Glue Stick (2) before connecting to mains power supply
- Never leave a glue gun unattended, always disconnect from power supply
- The hot nozzle must never come into contact with flammable materials such as paper, cardboard, plastic, wood etc.

Product Familiarisation

- 1. Nozzle
- 2. Glue Stick
- 3. Handle
- 4. Power Cord
- 5. Trigger
- 6. Mounting Points for Stand

Intended Use

Electric hot melt glue gun, using conventional glue sticks, for craft and hobby

Not intended for commercial use.

The tool must ONLY be used for its intended purpose. Any use other than those mentioned in this manual will be considered a case of misuse. The operator, and not the manufacturer, shall be liable for any damage or injury resulting from such cases of misuse. The manufacturer shall not be liable for any modifications made to the tool, nor for any damage resulting from such modifications

Unpacking Your Tool

- Carefully unpack and inspect your tool. Fully familiarise yourself with all its features and functions
- Ensure that all parts of the tool are present and in good condition. If any parts are missing or damaged, have such parts replaced before attempting to use this tool

Before Use

WARNING: Ensure the tool is disconnected from the power supply before attaching or changing any accessories, or making any adjustments.

- 1. Attach Stand (7) to glue gun using Mounting Points (6)
- 2. Insert a Glue Stick (2) into rear of tool. Push forward until slight resistance

Operation

WARNING: Always place the glue gun on its Stand (7) when not in use. Ensure that the nozzle cannot cause any damage to surrounding materials

- 1. Ensure tool is positioned on a stable horizontal surface
- 2. Plug tool into mains power supply

Note: The glue gun will automatically switch on when it is plugged into the

- 3. Wait 3-5 minutes for tool to reach normal operating temperature
- 4. Gently squeeze Trigger (5) to advance glue stick and expel molten adhesive 5. Release the Trigger to stop
- 6. Once gluing is complete, place tool upright on a flat surface.
- 7. Unplug the tool from the mains power supply

Notes:

- Do not attempt to remove glue stick. Any unused glue stick can remain in the tool
- · Always practice applying adhesive to scrap materials until confident
- As with all adhesives, performance depends on atmospheric conditions of the work area. Recommendations are for guidance only; actual conditions of use will vary
- Ensure surfaces to be bonded are dry, free from dust, grease and loose
- · Apply adhesive to one surface only. Bring the two surfaces together immediately. Hold the joint together for 20-30 seconds to complete the
- When gluing different materials, apply the adhesive to the least porous
- On cold materials, a better bond can be achieved by pre-warming before
- Applying adhesive in wayy lines is recommended when gluing textiles or

- Surplus adhesive can be trimmed with a sharp knife when cooled
- . Do not attempt to force glue sticks through with excessive use or force of the trigger. Under and over-heated glue can cause the glue gun to break and cause injury and burns to the user

Accessories

A range of accessories and consumables, including glue sticks 50pk are available from your Silverline stockist. Spare parts can be obtained from toolsparesonline.com

Maintenance

 $\underline{\ensuremath{\Lambda}}$ WARNING: ALWAYS disconnect from the power supply before carrying out any inspection, maintenance or cleaning.

General inspection

- Regularly check that all the fixing screws are tight
- Inspect the supply cord of the tool, prior to each use, for damage or wear. Repairs should be carried out by an authorised Silverline service centre. This advice also applies to extension cords used with this tool

- Keep your tool clean at all times. Dirt and dust will cause internal parts to wear quickly, and shorten the machine's service life
- Clean the body of your machine with a soft brush, or dry cloth
- Clean the tool casing with a soft damp cloth using a mild detergent. Do not use alcohol, petrol or strong cleaning agents
- Never use caustic agents to clean plastic parts

Storage

- Ensure all parts of the tool are completely cool before storing. Never wrap the power cord around a tool that has not completely cooled
- Store this tool carefully in a secure, dry place out of the reach of children

Contact

For technical or repair service advice, please contact the helpline on (+44) 1935 382 222

Web: www.toolstream.com

UK Address: Toolstream Ltd., Boundary Way, Lufton Trading Estate, Yeovil, Somerset, BA22 8HZ, United Kingdom

EU Address: Toolstream B.V., Holtum-Noordweg 11, Unit 4, 6121 RE Born, Netherlands

Disposal

Always adhere to national regulations when disposing of power tools that are $% \left(1\right) =\left(1\right) \left(1$ no longer functional and are not viable for repair.

- Do not dispose of power tools, or other waste electrical and electronic equipment (WEEE), with household waste
- Dispose of residual glue and unused glue sticks according to the glue manufacturer's recommendations
- Contact your local waste disposal authority for information on the correct way to dispose of power tools and chemicals